



## **DG1000Z Firmware Update**

*Date:* 04.25.2014

*Solution:*

### **Update the Bootloader File:**

1. Copy the AROWANAUpdate.GEL file from the DG1000Z(Software)Update (Bootloader) folder to the root directory of a USB flash drive
2. Power on the DG1000Z
3. A RIGOL logo will appear and below the logo will appear several ellipses (...), when the third point appears, press help repeatedly till the message "please insert USB disk with the upgrade file" appears



4. Insert the USB flash with the bootloader update file
5. After the update is complete, the DG1000Z will reboot automatically

### **Update the Normal File:**

6. Copy the AROWANAUpdate.GEL file from the DG1000Z(Software)Update (Normal) folder to the root directory of a USB flash drive
7. Power on the DG1000Z

8. A RIGOL logo will appear and below the logo will appear several ellipses (...), when the third point appears , press help repeatedly till the message "please insert USB disk with the upgrade file" appears



9. Insert the USB flash with the normal update file
10. After the update is complete, the DG1000Z will reboot automatically
11. After the update is complete , you can check the firmware information by pressing Utility > Down arrow to menu page 2/2 > System Info

**Note:** Don't power off or move the USB flash during updating



## Headquarters

RIGOL TECHNOLOGIES, INC.  
No.156,Cai He Village,  
Sha He Town,  
Chang Ping District, Beijing,  
102206 P.R.China  
Tel:+86-10-80706688  
Fax:+86-10-80705070  
Email: [support@rigol.com](mailto:support@rigol.com)

## USA

RIGOL TECHNOLOGIES,USA INC.  
7401 First Place, Suite N  
Oakwood Village  
OH 44164, USA  
Toll free: 877-4-RIGOL-1  
Office: (440) 232-4488  
Fax: (216)-754-8107  
Email: [info@rigol.com](mailto:info@rigol.com)

## EUROPE

RIGOL TECHNOLOGIES GmbH  
Lindbergh str. 4  
82178 Puchheim  
Germany  
Tel: 0049- 89/89418950  
Email: [info-europe@rigoltech.com](mailto:info-europe@rigoltech.com)