



Measuring FM Deviation with a Rigol DSA

Date: 02.19.2015

Solution: General purpose spectrum analyzers like the Rigol DSA series can be used to test the deviation of an FM signal.

In this example, we are going to measure the FM deviation of a 10MHz FM signal with a DSA815. This is Rigol's 1.5GHz spectrum analyzer.

NOTE: We are starting from Factory default settings. See the User's Guide for the instrument you are using to learn more about restoring factory defaults.

1. Set the center frequency of the analyzer to the carrier frequency of the FM signal.

Press **FREQ** > Press **Center Freq** > set **Center Frequency** using the scroll wheel or keypad

2. Set the Span to cover the expected frequency deviation of the input signal.

Press **SPAN** > press **Span** > set using the scroll wheel or keypad


3. Set the resolution bandwidth (RBW) to provide the resolution that is required for the test.

Press **BW/Det** > Press **RBW** > set using the scroll wheel or keypad

4. Enable a second trace type as Max Hold. We will leave trace 1 (yellow) as a Clear Write type. This will display the input values in “real time” and trace 2 (purple) will provide a histogram of the max values achieved for all scans.

Press Trace/P/F > Select Trace 2 > Set Trace Type to Max Hold

5. Let the instrument scan for a period of time long enough to build a complete envelope of the modulated signals frequency deviation.



The DSA815 has 10 divisions on the display. The span in this example is 20kHz. So, each division is 2kHz. In this example the FM deviation is approximately 2kHz.



Headquarters

RIGOL TECHNOLOGIES, INC.
No.156,Cai He Village,
Sha He Town,
Chang Ping District, Beijing,
102206 P.R.China
Tel:+86-10-80706688
Fax:+86-10-80705070
Email: support@rigol.com

USA

RIGOL TECHNOLOGIES,USA INC.
102000 SW Allen Blvd, Suite C
Beaverton
OR 97005, USA
Toll free: 877-4-RIGOL-1
Office: (440) 232-4488
Fax: (216)-754-8107
Email: info@rigol.com

EUROPE

RIGOL TECHNOLOGIES GmbH
Lindbergh str. 4
82178 Puchheim
Germany
Tel: 0049- 89/89418950
Email: info-europe@rigoltech.com